



ABN 43 064 478 842

231 Osborne Avenue Clayton South, VIC 3169  
PO Box 1548, Clayton South, VIC 3169  
t 03 9265 7400 f 03 9558 0875  
freecall 1800 680 680  
www.tmgtestequipment.com.au

## Test & Measurement

- > sales
- > rentals
- > calibration
- > repair
- > disposal

## Complimentary Reference Material

This PDF has been made available as a complimentary service for you to assist in evaluating this model for your testing requirements.

TMG offers a wide range of test equipment solutions, from renting short to long term, buying refurbished and purchasing new. Financing options, such as Financial Rental, and Leasing are also available on application.

TMG will assist if you are unsure whether this model will suit your requirements.

Call TMG if you need to organise repair and/or calibrate your unit.

If you click on the "Click-to-Call" logo below, you can call us for FREE!

TMG Corporate Website

TMG Products Website



Click-to-Call  
TMG Now



Product Lifecycle Management System

### Disclaimer:

All trademarks appearing within this PDF are trademarks of their respective owners.





## 403 LA POWER AMPLIFIER

### 3 Watt Linear UHF Amplifier For Signal Distribution

- 150KHz – 300MHz  
Frequency Range
- Rugged Compact Design
- Operates into any load
- Low Distortion

#### High Reliability

Complete stability and instantaneous fail-safe protection ensure operation in to mismatch and overdrive conditions.

The 403 LA will withstand a + 13dBm Input signal for all load conditions.

The 403LA Broadband Amplifier is a rugged source of RF power suitable for a variety of UHF signal distribution and general laboratory applications. It is a compact fully solid state design. It features low-level intermodulation distortion and inherent protection against short and open circuit loads. The 403 LA amplifies the inputs of AM, FM, SSB, pulse and other complex modulations within its output and bandwidth capability.

#### Flexible Operation

The 403LA produces 3 Watts of Class A linear output power over a frequency range of 150 KHz to 300 MHz with a nominal gain of 37 dB (+/-1dB). In order to provide exceptionally low levels of IMD, highly linear RF devices are used, with feedback, in the driver and output amplifier stages. All harmonics are more than 25 dB below the fundamental frequency at 2.7 Watts Pout.

#### Rugged Design

An integral power supply allows for operation directly from an input of 115/230 V single phase. Both the power supply and the forced air cooling are conservatively designed for operation over a wide temperature range.



150 Lucius Gordon Drive.  
Rochester, NY 14586  
Tel: (585) 214 0598  
Fax: (585) 214 0580  
WWW. ElectronicsAndInnovation.com

# 403 LA POWER AMPLIFIER

## Class of Operation

Class A

## Frequency Range

150 KHz to 300MHz

## Rated Output Power

3.0 Watts

## Gain

37 dB

## Gain Flatness

+/- 2dB

## Input For Rated Output

1 mw (0dBm)

## Input Impedance / VSWR

50Ω 1.5:1

## Output Impedance / VSWR

50Ω 2.5:1

## Harmonic Level

< -25 dBc @ 2.7 W output

## Ruggedness

∞:1 VSWR

## IP3

+45 dBm Typical

## Noise Figure

9 dB Typical

## Spurious Output: <-60dBc

## Primary Power:

85 – 264 VAC 47-63 Hz.

## Temperature Range

0 to 45 degrees C

## Cooling

Forced Air

## Weight

7 lbs. (3.2 Kg)

## Front Panel

Controls: AC On/Off

Indicators: AC Power On

Connectors: RF Input/Output (BNC)

## Accessories Supplied

Rack mounting adaptors

Operation Manual

AC line cord

RF POWER AMPLIFIERS

The ruggedness and reliability you counted on  
from the "old ENI Amplifiers" are back!



150 Lucius Gordon Drive.

Rochester, NY 14586

Tel: (585) 214 0598

Fax: (585) 214 0580

WWW. ElectronicsAndInnovation.com